



## PRODUCT SUMMARY

# SKY68035-11: Massive IoT Half-duplex Front-end Module with Coupler

## Applications

- Low-power, low-data-rate cellular IoT
- Half-duplex operation (HD-FDD):
  - LTE-M
  - NB-IoT
- Universal modem products:
  - Low-band: 5, 8, 12, 13, 14, 17, 18, 19, 20, 26, 28, 71, 85
  - Mid-band: 1, 2, 3, 4, 25, 39, 65, 66, 70, NTN
- Broadband operation on TRX to ANT paths, from 400 MHz to 2.7 GHz

## Features

- Output power: +24.5 dBm at antenna, optimized to support LTE for 1 RB to 6 RB
- Broadband PA supporting APT mode of operation or VCC fixed supply: 2.2 V to 4.5 V
- Integrated TX low-pass filters for optimized harmonic rejection
- Integrated SP6T antenna TX/RX switch
- Low leakage current: 0.4  $\mu$ A
- Adaptive biasing scheme for maximum PA efficiencies
- MIPI® RFFE control interface, 2.0 compliant
- Operating temperature range:  $-40^{\circ}\text{C}$  to  $+105^{\circ}\text{C}$
- Low-profile 24-pin, 3.0 x 3.0 x 0.67 mm package MSL3, 260  $^{\circ}\text{C}$  per JEDEC J-STD-020
- For RoHS and other product compliance information, see the [Skyworks Certificate of Conformance](#).

## Description

The SKY68035-11 is a hybrid, multi-band multi-chip RF front-end (RFFE) module supporting LTE-M/NB-IoT transceiver platforms.

- The module integrates the entire RF front end necessary for an LTE multi-band radio operating in low-band (5, 8, 12, 13, 14, 17, 18, 19, 20, 26, 28, 71, 85) and mid-band (1, 2, 3, 4, 25, 39, 65, 66, 70, NTN) frequencies, including broadband PA with bias

controller, TX lowpass harmonic filter, antenna switch, and MIPI RFFE controller.




Figure 1. Block Diagram

## TX Section

The PA load-line is optimized for high efficiency while simultaneously meeting 3GPP ACLR and emissions mask specifications with LTE up to 6 RB. An integrated LPF rejects the PA and transceiver harmonics and minimizes post PA losses for optimized transmit current consumption. Out-of-band emissions performance is emphasized by the design to be 3GPP-compliant for low-band and mid-band frequencies.

## TRX Paths

The four TRX ports are additional broadband ports that can be used symmetrically for either TX or RX operation.

## MIPI RFFE Controller Interface

The SKY68035-11 functional operation is fully controllable by a single MIPI interface which is used to configure the MB and LB PAs in various optimized bias modes, provide band selection, and control the antenna switch.

## Ordering Information

Part Number	Part Description
SKY68035-11	Massive IoT Half-Duplex Front-end Module (FEM) with Coupler

Copyright © 2025, Skyworks Solutions, Inc. All Rights Reserved.

Information in this document is provided in connection with Skyworks Solutions, Inc. ("Skyworks") products or services. These materials, including the information contained herein, are provided by Skyworks as a service to its customers and may be used for informational purposes only by the customer. Skyworks assumes no responsibility for errors or omissions in these materials or the information contained herein. Skyworks may change its documentation, products, services, specifications or product descriptions at any time, without notice. Skyworks makes no commitment to update the materials or information and shall have no responsibility whatsoever for conflicts, incompatibilities, or other difficulties arising from any future changes.

No license, whether express, implied, by estoppel or otherwise, is granted to any intellectual property rights by this document. Skyworks assumes no liability for any materials, products or information provided hereunder, including the sale, distribution, reproduction or use of Skyworks products, information or materials, except as may be provided in Skyworks' Terms and Conditions of Sale.

THE MATERIALS, PRODUCTS AND INFORMATION ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, WHETHER EXPRESS, IMPLIED, STATUTORY, OR OTHERWISE, INCLUDING FITNESS FOR A PARTICULAR PURPOSE OR USE, MERCHANTABILITY, PERFORMANCE, QUALITY OR NON-INFRINGEMENT OF ANY INTELLECTUAL PROPERTY RIGHT; ALL SUCH WARRANTIES ARE HEREBY EXPRESSLY DISCLAIMED. SKYWORKS DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. SKYWORKS SHALL NOT BE LIABLE FOR ANY DAMAGES, INCLUDING BUT NOT LIMITED TO ANY SPECIAL, INDIRECT, INCIDENTAL, STATUTORY, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS THAT MAY RESULT FROM THE USE OF THE MATERIALS OR INFORMATION, WHETHER OR NOT THE RECIPIENT OF MATERIALS HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

Skyworks products are not intended for use in medical, lifesaving or life-sustaining applications, or other equipment in which the failure of the Skyworks products could lead to personal injury, death, physical or environmental damage. Skyworks customers using or selling Skyworks products for use in such applications do so at their own risk and agree to fully indemnify Skyworks for any damages resulting from such improper use or sale.

Customers are responsible for their products and applications using Skyworks products, which may deviate from published specifications as a result of design defects, errors, or operation of products outside of published parameters or design specifications. Customers should include design and operating safeguards to minimize these and other risks. Skyworks assumes no liability for applications assistance, customer product design, or damage to any equipment resulting from the use of Skyworks products outside of Skyworks' published specifications or parameters.

Skyworks, the Skyworks symbol, Sky5®, SkyOne®, SkyBlue™, Skyworks Green™, ClockBuilder®, DSPLL®, ISModem®, ProSLIC®, SiPHY®, and RFelC® are trademarks or registered trademarks of Skyworks Solutions, Inc. or its subsidiaries in the United States and other countries. Third-party brands and names are for identification purposes only and are the property of their respective owners. Additional information, including relevant terms and conditions, posted at [www.skyworksin.com](http://www.skyworksin.com), are incorporated by reference.